

Casio 140CR Cash Registers

MAC Clear ECR

- a) Turn power off at wall
- b) Set mode key to **OFF**
- c) Remove Memory Batteries
- d) Wait approx 2 minutes
- e) Turn power on at wall
- f) Set mode key to **REG**
- g) Insert Memory Batteries
- h) Follow prompts on printout
- i) Enter 0 for english
- j) Press [**Cash**]
- k) Enter date DD:MM:YY
- l) Enter time 24 hour format HH:MM eg. 5 pm = 17:00

Set Register for Australian GST settings (Only valid after a MAC procedure)

- a) Turn key to **Z**
- b) Enter 01 01 20 01
- c) Press [**Sub Total**]
- d) Press [**Cash**]

Set ECR to operate as Receipt or Journal

- a) Turn key to **Program**
- b) Press **1**
- c) Press [**Sub Total**]
- d) Then either
Press **1** (for Receipt) OR
Press **0** (for Journal)
- e) Press [**CH**] key
- f) Press [**Sub Total**]

Set Prices to Departments

- a) Turn key to **Program**
- b) Press **1** Press [**Sub Total**]
- c) Enter **Price**
- d) Press the [**Department**] you are programming
- e) Repeat steps c) and d) for more departments
- f) Press [**Sub Total**] when finished

Set Departments to be SIS (Single Item Sale)

- a) Turn key to **Program**
- b) Press **3**
- c) Press **[Sub Total]**
- d) Enter **1**
- e) Press the **[Department]** you are programming
- f) Repeat steps d) and e) for more departments
- g) Press **[Sub Total]** when finished

Set Departments for GST or Non GST

- a) Turn key to **Program**
- b) Press **1**
- c) Press **[Sub Total]**
- d) Press **[Tax Pgm]**
- e) Press Either
 [RA/MR] for GST or
 [#/NS] for Non-GST
- f) Press the **[Department]** you are programming
- g) Repeat steps d) and e) for more departments
- h) Press **[Sub Total]** when finished